

8 Port GPS Timing Reference Splitter

DESCRIPTION

The S18GT has been specifically designed for the L band frequency. Built to eliminate the cost of multiple antennas and long cable runs in wireless installations, it makes it possible to use a single GPS referencing antenna and cable arrangement for multiple synchronized systems.

The S18GT features an antenna DC bias select circuit. This allows for the active antenna DC input to be applied to any or all RF outputs. With this feature, one DC voltage will be chosen to power the antenna while other inputs will be switched to DC blocked outputs with 200 Ohm resistive loads to ground. Designed for redundancy, if the selected DC bias input should fail or is removed, the DC bias will automatically switch to another DC input to ensure an uninterrupted supply to the active antenna.

The S18GT is an amplified device that is configured for 00dB or 10dB gain.

FEATURES

- Amplified to Offset Splitter Losses
- Standard Antenna DC Bias Select
- RoHS/REACH/WEEE Compliant



S18GT Data Sheet

059-FSA-AMQ-AAS-AGZ-002
04/17/2020
www.gpssource.com

AS9100 and ISO 9001 Compliant Company

1 S18GT Electrical Specifications

Table 1-1. Electrical Specifications

Operating Temperature -40°C to 85°C

Parameter	Conditions	Min	Typ	Max	Units	
Frequency Range	Ant: Any Port; Unused Ports: 50Ω ⁽¹⁾	1.1		1.7	GHz	
Gain	Ant: Any Port; Unused Ports: 50Ω	00dB	-3	0	3	dB
		10dB	7	10	13	
Input/Output SWR	All Ports 50Ω			2	—	
Noise Figure	Amplified Ant: Any Port; Unused Ports: 50Ω, Gain = 0dB			3	dB	
Gain Compression Point (IP1dB)	Gain = 0dB	-32			dBm	
3rd Order Intercept (IIP3) (Gain = 0dB)	f1 = 1600.42MHz f2 = 1625.42MHz 2f1 – f2 = fL1	-24			dBm	
RF Input (Damage Threshold)	Maximum RF input without damage			0	dBm	
Amp. Balance	[OUT1 – OUT8] Ant: Any Port; Unused Ports: 50Ω			1	dB	
Phase Balance	Phase (OUT1 – OUT8) Ant: Any Port; Unused Ports: 50Ω			1	Degree	
Delay	Ant: Any Port; Unused Ports: 50Ω, L1			5	ns	
Isolation (Gain = 0dB)	Adjacent Ports: Ant – 50Ω	28			dB	
	Opposite Ports: Ant – 50Ω	34				
DC IN	DC Input on Any RF Output	3		12	VDC	
Device Current	Current Consumption of Active Device (excludes Ant. Cur.)		18	20	mA	
Ant/Thru Current ⁽²⁾	Max Source DC Current Through Device			250	mA	

Notes: 1. Frequency range includes GPS L1, GLONASS L1, and GALILEO E1.

2. Maximum current allowed from the DC source through the S18GT when output of S18GT is short circuited.

2 Performance Data

2.1

Figure 2-1. Frequency Response (10dB)




Figure 2-2. Output SWR (10dB)




Figure 2-3. Frequency Response (0dB)





Figure 2-4. Output SWR (0dB)



3 Operational Description

3.1 RF Signal Processing System

The RF signal processing system consists fundamentally of amplification stages and classical Wilkinson Splitter elements which divide the RF signal from the antenna input evenly between eight RF output ports. The standard gain is 00dB.

3.2 Gain Option

In the Amplified High Isolation Configuration (standard 00dB), 50 Ω signal attenuators are in the RF output paths to provide additional isolation between each RF port. The S18GT does not require 50 Ω terminations on unused ports in order for the splitter to operate correctly. This standard configuration is chosen if it is possible for spurious emissions from one GPS receiver on one port of the splitter to cause interference with GPS receivers connected to other output ports.

To some extent, the port-to-port isolation performance is a function of the input-to-output gain. The port-to-port isolation is maximized when the gain is 00dB.

3.3 Antenna DC Bias Select

GPS Source RF signal splitters are unique relative to other generic RF signal splitters as they typically operate in conjunction with an active GPS antenna (a GPS antenna that includes an integrated Low Noise Amplifier). Consequently, a GPS RF signal splitter must have provisions for managing the DC voltage to the active GPS antenna.

The S18GT splitter requires a DC voltage be applied to one or more of the RF output ports by way of the RF connector center conductor. If DC voltages are applied to more than one of the RF output ports, the S18GT DC bias select circuit will choose one of these DC inputs to power the active circuitry of the S18GT and will also pass this DC voltage through the splitter to the center conductor of the RF input port. Ports without an external DC voltage applied, or from which an external DC voltage is removed, are internally pulled-down to ensure that the false input voltage indications do not occur. The DC voltage available on the RF input port can be used to power the application's active antenna.

The DC voltages applied to the RF outputs that are not chosen by the DC bias select circuitry will automatically switch through an RF choke to 200 Ω DC loads. The DC bias select circuit will always select the DC voltage on the lowest numbered RF port that has a DC voltage applied to power the S18GT and the application's antenna. If the chosen DC input is removed or fails, the DC bias select circuit will automatically switch to the next higher numbered RF port to which a DC voltage is applied.

Example 1: Assume DC voltages are applied to RF outputs 1, 3, and 4. In this scenario, the DC voltage on port 1 will be used to power the S18GT and the application antenna. Ports 3 and 4 will be switched to 200 Ω DC loads.

Example 2: Now assume the DC voltage on port 1 is removed. The S18GT will automatically terminate the input internally with a pull-down resistor and switch the operation of the splitter and antenna to the DC voltage applied to the next high numbered port with a DC voltage applied, port 3. Port 4 will remain switched to a 200 Ω load.

4 S18GT Connection

To install the S18GT, connect the coaxial cable feeding the active GPS antenna prior to connecting the RF outputs. Once the antenna coaxial cable is attached, coaxial cables with or without DC voltages can be connected to the outputs.




At least one coaxial cable connected to any output of the device must provide a DC voltage suitable for operating the active GPS antenna and the S18GT.

5 Certifications and Approvals

Certifications and Approvals	
EMC/Emissions	FCC part 15B and R&TTE equivalent
Safety/Low Voltage	EN60950-1
Environmental	IEC 60529, IP55


6 Product Code Decoder



Note: To have product/part codes customized to meet exact needs, contact GPS Source at GPSS-Sales@gd-ms.com or visit the website at www.gpssource.com.

7 Mechanical Drawing

S18GT — L Band Signal Splitter



GPS Source Part No. S18GT	Finish N/A	Size C	Mass	Tolerances	
Description S18GT W/DC BIAS SELECT	Material N/A	3 rd Angle Projection 		Linear .X = ±0.100 .XX = ±0.010	Angular ±1° RADII See Linear

All materials and finishes shall comply with European Union RoHS and are lead free. Dimensions are in inches unless otherwise specified.

S18GT Data Sheet

059-FSA-AMQ-AAS-AGZ-002

Page 9 of 9, 04/17/2020



2121 Executive Cir., Ste 100
Colorado Springs, CO 80906
Phone: (+1)(719) 421.7300
Toll Free: (+1)(866) 289.4777
GPSS-Sales@gd-ms.com
www.gpssource.com

AS9100 and ISO 9001 Compliant Company



© 2017 GPS Source, Inc. All rights reserved.

GPS Source, Inc., GPS Live Inside, GPS Source logo, and other GPS Source, Inc. products, brands, and trademarks mentioned in this document are property of GPS Source, Inc. and/or its affiliates in the United States and/or other countries. Other products, brands, and trademarks are property of their respective owners/companies. Any rights not expressly granted herein are reserved.

DISCLAIMER: The materials in this document could include inaccuracies or typographical errors and are subject to change at any time. The materials are provided "as is" without warranty of any kind. To the maximum extent permitted by applicable law, GPS Source, Inc. and its suppliers hereby disclaim all warranties, either expressed or implied, and conditions with respect to the materials, their quality, performance, suitability, merchantability, fitness for a particular purpose, title, and non-infringement. LIMITATION OF LIABILITY: IN NO EVENT WILL GPS SOURCE, INC. AND ITS SUPPLIERS BE LIABLE FOR INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES, WHETHER IN AN ACTION OF CONTRACT OR TORT, ARISING OUT OF THE USE OR INABILITY TO USE THE MATERIALS AVAILABLE IN THIS DOCUMENT, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. IN PARTICULAR AND WITHOUT LIMITATION, GPS SOURCE, INC. SHALL HAVE NO LIABILITY FOR ANY LOSS OF USE, DATA, INCLUDING THE COSTS OF RECOVERING SUCH DATA, OR PROFITS.